

300W - 4000W 12V | 24V to 230V Car Inverter

- Charge any device (laptops, household electronics, TVs, etc.) on the go.
- Stable & safe conversion.
- Pure sine wave output.
- Protections: Over / under voltage, overheating, overload, rear pole short circuit.
- Built with high quality materials. Protective metallic case.
- Easy to store & transport.
- Digital display shows output voltage (models: 500W, 1000W, 1500W, 2500W, 4000W).
- LED indicators for working / errors.
- Cables included.
- Additional output: 1x USB output.

Technical Specifications

Power	300 W	500 W	1000 W		1500 W	2500 W	4000 W
Peak Power	600 W	1000 W	2000 W		3000 W	5000 W	8000 W
Surge Current when power on	< 50 A	< 83.3 A	< 166.6 A	< 83.3 A	< 250 A	< 416.6 A	< 666.6 A
No-load Current	< 0.8 A	< 0.6 A	< 0.8 A	< 0.4 A	< 1.2 A	< 1.6 A	< 1.8 A
Input Voltage	12 V		12 V	24 V	12 V		
Output Voltage	230V AC						
Output Frequency	50 Hz						
Output Distortion THD	< 3%						
Rated / Max Output Efficiency	> 94.5% / 94.8% (70% load)						
Outputs	1x Schuko + 1x USB			2x Schuko + 1x USB			
Waveform	Pure Sine Wave						
Dimension LxWxH (mm)	210x115x63	270x151x85	325x165x92		390x167x90	415x165x82	467x200x154
Weight	0.92 kg	1.9 kg	3.2 kg		4.2 kg	7.2 kg	9.2 kg
Compatible Batteries	Any 12V batteries			Any 24V bat.	Any 12V batteries		
Working Temperature	-10° to +50						

Models:



Due to continuous product improvements, program specifications are subject to change without notice

Address: Holland, City: Wassenaar, Dr. Mansveltkaade Street 48, Postal code: 2242XM